University of Central Florida

STARS

UCF Patents

Technology Transfer

7-31-2007

Active Transient Voltage Compensator for Fast Transient Response Improvement

Issa Batarseh

Shamala Chickamenahalli Intel Corporation

Edward Stanford Intel Corporation

Xiangcheng Wang University of Central Florida

Find similar works at: https://stars.library.ucf.edu/patents University of Central Florida Libraries http://library.ucf.edu

This Patent is brought to you for free and open access by the Technology Transfer at STARS. It has been accepted for inclusion in UCF Patents by an authorized administrator of STARS. For more information, please contact STARS@ucf.edu.

Recommended Citation

Batarseh, Issa; Chickamenahalli, Shamala; Stanford, Edward; and Wang, Xiangcheng, "Active Transient Voltage Compensator for Fast Transient Response Improvement" (2007). *UCF Patents*. 663. https://stars.library.ucf.edu/patents/663



US007251113B1

(12) United States Patent

Batarseh et al.

(54) ACTIVE TRANSIENT VOLTAGE **COMPENSATOR FOR IMPROVING CONVERTER FAST TRANSIENT RESPONSE**

- (75) Inventors: Issa Batarseh, Orlando, FL (US); Xiangcheng Wang, Orlando, FL (US); Shamala A. Chickamenahalli, Chandler, AZ (US); Edward Stanford, Dupont, WA (US)
- (73) Assignee: Research Foundation of The University of Central Florida, Orlando, FL (US)
- (*) Notice: Subject to any disclaimer, the term of this patent is extended or adjusted under 35 U.S.C. 154(b) by 145 days.
- Appl. No.: 11/067,261 (21)
- (22) Filed: Feb. 25, 2005
- (51) Int. Cl. H02H 7/122 (2006.01)
- (52)
- (58)Field of Classification Search 361/111

See application file for complete search history.

US 7,251,113 B1 (10) Patent No.:

(45) Date of Patent: Jul. 31, 2007

References Cited

U.S. PATENT DOCUMENTS

6,903,914 B1* 6/2005 Moussaoui 361/111

* cited by examiner

(56)

Primary Examiner-Michael Sherry

Assistant Examiner-Lucy Thomas

(74) Attorney, Agent, or Firm-Brian S. Steinberger; Phyllis K. Wood; Law Offices of Brian S. Steinberger, P.A.

(57)ABSTRACT

A direct current to direct current (DC-to-DC) converter having an active transient voltage compensator (ATVC) coupled with the DC-to-DC converter output terminal to improve a fast transient response of the DC-to-DC converter. The active transient voltage compensator compensates the DC output only during transient operation The ATVC includes a transformer for reducing the ATVC current stresses to improve the compensator efficiency and injecting, absorbing high slew rate current, and a controller circuit for controlling ATVC operation in steady state and normal operation in transients. During step-up load the ATVC operates as a buck converter and during step-down load, the ATVC operates as a boost converter while the main converter operates at low switching frequency for good efficiency.

11 Claims, 14 Drawing Sheets









FIG. 2 PRIOR ART



FIG. 3



FIG. 4 A



FIG. 4B





FIG. 6A



FIG. 6B







FIG. 6D



FIG. 6E



FIG. 7



FIG. 8



FIG. 9



FIG. 10



FIG. 11













FIG.13B



FIG. 14



FIG. 16

10

ACTIVE TRANSIENT VOLTAGE COMPENSATOR FOR IMPROVING CONVERTER FAST TRANSIENT RESPONSE

FIELD OF THE INVENTION

This invention relates to voltage converters and, in particular, to methods, systems, apparatus and devices for increasing the fast transient response, power density and efficiency of a DC-to-DC converter.

BACKGROUND AND PRIOR ART

Widely applied to various electronic products, a DC-to-DC converter provides the functions of regulating the volt- 15 age level from a DC input voltage, such as boost or buck voltage conversion, and of maintaining the regulated voltage at the desired level. Under the transient high slew rate load, the unbalanced current between the DC-to-DC converter and output load current is provided by filter capacitors. There are 20 two voltage spikes under the transient load. The first output voltage spike relates to equivalent series resistance (ESR), equivalent series inductance (ESL) of filter capacitors and slew rate of the load; the second output voltage spike is determined by to the energy stored in filter inductance and 25 filter capacitance. Commonly, a large number of bulk and ceramic capacitor mounted close to load is used to reduce the output impedance for voltage spikes suppression. But it is not a suitable solution for higher slew rate load; low output voltage high output current applications because of 30 the cost and size limitation. Output voltage spikes are the products of the output impedance, or called load line, and the output current. High bandwidth of a converter and small output impedance helps to reduce its voltage spikes under high slew rate load and high bandwidth also helps to reduce 35 its output impedance.

The bandwidth of a converter is mainly limited by three delay times: the filter inductor capacitance (LC) delay time, controller delay time, and propagation delay time. Examples of propagation delays in DC-to-DC converters include sig-40 nal sensing delay, driver delay, control IC delay, and extra optocoupler delay in isolated DC-to-DC converter. The key limitation of the current slew rate of the converter is the equivalent filter inductance. A known solution for improving the output slew rate involves increasing the switching frequency to reduce the equivalent inductance. However, the increase in switching frequency results in deterioration of converter efficiency. An attractive solution is extra dynamic channel with high switching frequency operation because it only operates during transient periods.

Current injection topology, such as linear mode current injection topology and switching mode current injection topology, handles the transient current and the main converter handles the static current. It is an attractive extra dynamic channel for transient response improvement tech- 55 nique because this technique allows high slew rate current injection in step-up load and energy absorption in step-down load while the main converter maintaining an optimal converter design for improved efficiency.

FIG. 1 is a schematic diagram a DC-to-DC converter 60 including a main converter 12 and incorporating a linear mode current injection topology 14 according to the prior art. The linear mode current injection topology 14 solution injects high slew rate current I_{Lin} to the DC-to-DC converter 10 during step-up operation and clamps the output voltage 65 V_o using resistive dissipation. However, the efficiency of the DC-to-DC converter 10 is reduced due to the large conduc-

2

tion loss in linear mode current injection topology related with the high voltage drop $(V_{in}-V_O)$ and the high current stress (I_O-I_p) .

FIG. 2 is a schematic diagram of switching mode current injection topology 16 of the prior art. Switching mode current injection topology 16 operates at high frequency to reduce the filter inductance L_{sw} to achieve a high slew rate current I_{sw} injection during step-up load as a buck converter. During step-down operation recycles energy to the input voltage V1 as a boost converter. However, switching mode current injection topology results in a large power loss due to high current stress (I_O-I_p) combined with the high switching frequency operation.

The high power loss resulting from use of current injection topology is the impediment to wide scale application because the imbalance between the output current and the current provided by the main converter all conduct through the current injection topology. For current injection topology, a large conduction loss in linear mode **14** or switching loss in switching mode **16** results due to the high current stress and the high switching frequency. For these reasons, current injection topology is not a good solution for high slew rate current, high efficiency power conversion application, especially for converters having low voltage, high current output.

The present invention advances the art by providing a method, system, apparatus and device for reducing the output impedance for voltage spikes suppression by providing an active transient voltage compensator for use with isolated or non-isolated DC-to-DC converters. The active transient voltage compensator injects the voltage source instead of the current source in prior arts current injection topology. During transient periods, the active transient voltage compensator provides high slew rate current due to small leakage inductance of the transformer.

SUMMARY OF THE INVENTION

A primary objective of the invention is to provide a new method, system, apparatus and device to improve the fast transient response of a DC-to-DC converter.

A secondary objective of the invention is to provide a new method, system, apparatus and device to maintain the compensator only engaged in transients, no operation in steady state.

A third objective of the invention is to provide a new method, system, apparatus and device to improve the fast transient response of a DC-to-DC converter while keeping main converter high efficiency with low operating frequency.

A forth objective of the invention is to provide a new method, system, apparatus and device to provide a transformer to reduce the current handled by the compensator to reduce conduction loss and switching loss to improve the efficiency of the compensator.

A fifth objective of the invention is to provide a new method, system, apparatus and device to provide a compensator to reduce the output impedance of the DC-to-DC converter for fast transient response.

Further objects and advantages of this invention will be apparent from the following detailed description of preferred embodiments, which are illustrated, schematically in the accompanying drawings. 20

4∩

50

55

BRIEF DESCRIPTION OF THE FIGURES

FIG. **1** is a schematic diagram of a prior art DC-to-DC linear mode current injection topology.

FIG. **2** is a schematic diagram of a prior art DC-to-DC $^{-5}$ switching mode current injection topology.

FIG. **3** is a schematic diagram of a DC-to-DC converter using the active transient voltage compensator of the present invention.

FIG. **4**A is a schematic diagram of a DC-to-DC converter of FIG. **3** including the magnetizing inductance, the resistance of magnetizing inductance and leakage inductance L_{LK} of the active transient voltage compensator transformer.

FIG. **4**B is a schematic diagram of a DC-to-DC converter of FIG. **3** including the controller block diagram of the main converter and the controller block diagram of the active transient voltage compensator.

FIG. **5** is a graph illustrating graphical representations of the operational voltage and current waveforms of the DC-to-DC converter of FIG. **4**A with respect to time during step-up load mode, steady-state and step-down load mode operations.

FIG. **6**A is a schematic of the step-up load mode operation of the active transient voltage compensator corresponding to $_{25}$ time **t1** to **t1'** as shown on the graph of FIG. **5**.

FIG. **6**B is a schematic of the step-up load mode operation of the active transient voltage compensator corresponding to time **t1**' to **t2** as shown on the graph of FIG. **5**.

FIG. 6C is a schematic of the steady state operation of the $_{30}$ active transient voltage compensator corresponding to time t3 to t4 as shown on the graph of FIG. 5.

FIG. **6**D is a schematic of the step-down load mode operation of the active transient voltage compensator corresponding to time t**4** to t**4**' as shown on the graph of FIG. 35 **5**.

FIG. **6**E is a schematic of the step-down load mode operation of the active transient voltage compensator corresponding to time **t4'** to **t5** as shown on the graph of FIG. **5**.

FIG. **7** is a schematic diagram of an experimental DC-to-DC converter using the active transient voltage comparator according to the present invention.

FIG. **8** shows the operational currents of the ATVC circuit in the experimental DC-to-DC converter of FIG. **7** during ⁴⁵ step-up load mode.

FIG. 9 shows the operational currents of the ATVC circuit in the experimental DC-to-DC converter of FIG. 7 during step-down load mode.

FIG. **10** show a comparison between the ATVC operational current I_{ATVC} , the main converter output current I_1 and the DC-to-DC converter output current I_O during step-up load mode.

FIG. **11** show a comparison between the ATVC operational current I_{ATVC} , the main converter output current I_1 and the DC-to-DC converter output current I_O during step-down load mode.

FIGS. **12**A and **12**B are graphs of the DC-to-DC converter output voltage V_o during step-up load mode with ATVC and ₆₀ without ATVC, respectively.

FIGS. **13**A and **13**B are graphs of the DC-to-DC converter output voltage V_O during step-down load mode with ATVC and without ATVC, respectively.

FIGS. **14**, **15** and **16** are schematic diagrams of alternative 65 DC-to-DC circuits utilizing the ATVC of the present invention.

DESCRIPTION OF THE PREFERRED EMBODIMENTS

Before explaining the disclosed embodiments of the present invention in detail it is to be understood that the invention is not limited in its application to the details of the particular arrangements shown since the invention is capable of other embodiments. Also, the terminology used herein is for the purpose of description and not of limitation.

The following is a list of the reference numbers used in the drawings and the detailed specification to identify components:

Reference No. Component

10 Prior art DC-to-DC converter

12 Main converter

- 14 Linear mode current injection topology
- 16 Switching mode current injection topology
- 100 DC-to-DC converter
- 110 Main converter
- 120 DC-to-DC converter with controller block diagram
- **150** Active transient voltage compensator (ATVC)
- 160 Main converter controller
- 161 Step up controller for ATVC
- **162** Step down controller for ATVC
- **163** Logic block for ATVC
- **164** ATVC controller
- 210 Operational current waveform
- 212 Minimum current I_{min}
- **213** Output current I_{Ω} ramp up
- **214** Main converter output current I_1 increase
- **216** Maximum output current I_{max}
- **217** Output current I_{O} decrease
- **218** Main converter output current I_1 ramp down
- 220 Reference voltage waveform
- 221 Reference voltage Vref1
- 222 Reference voltage Vref
- 223 Reference voltage Vref2
- **230** ATVC current waveform I_{ATVC}
- **240** Transformer primary current I_{1N} waveform
- **250** Transformer magnetizing inductance current I_{LM} waveform

260 Q_{a1} driver signal voltage waveform

270 Q_{a2} driver signal voltage waveform

The method, system, apparatus and device of the present invention reduce output voltage spikes in transients and improve the transient response by providing an active transient voltage compensator (ATVC) for use with isolated or non-isolated DC/DC converters. FIG. **3** is a schematic diagram of a conventional DC-to-DC converter **100** incorporating the active transient voltage compensator **150** of the present invention. The components of the ATVC differ from the prior art linear and switching mode current injection topologies by the inclusion of the transformer T_r in addition to the synchronous rectifiers Q_{a1} and Q_{a2}. FIG. **4**A is a schematic according to FIG. **3** including the magnetizing inductance L_M resistance R_{LM} of magnetizing inductance, and leakage inductance L_{LK} of the ATVC transformer T_r.

FIG. 4B is a schematic diagram of a DC-to-DC converter of FIG. 3 including the controller block diagram 160 of the main converter 110 and the controller block diagram 164 of the active transient voltage compensator 150. The main converter 110 regulates the output voltage level by the close loop controller 160 with reference voltage Vref 222, which feedbacks output voltage Vo and output current I1 with the gain Gm. ATVC controller 164 has two controllers: step-up controller 161 with reference voltage Vref1 221 and stepdown controller 162 with reference voltage Vref2 223. The step-up controller generates the driver signal of Qa1 only in the step-up load mode and the step-down controller generates the driver signal of Qa2 only in the step-down load mode. The logic block 163 in ATVC controller 164 is used to keep no ATVC operation in steady state and generate complimentary driver signal for Qa2 in step-up load mode and complimentary driver signal for Qa1 in step-down load mode in transient periods.

As identified in FIGS. 3 and 4A, V_{in} is the input voltage 10 applied to the main converter 110. The main converter 110 has an output voltage V_{01} and a corresponding output current I_1 . The main converter 110 includes a filter capacitor C_1 connected across the output. The filter capacitor C_1 and the equivalent series inductance L_{C1} and equivalent series resistance R_{C1} of filter capacitor C_1 are illustrated as serial components connected in parallel across the output of the main converter 110. The parasitic parameters of trace, socket are illustrated as resister R_P and inductor L_P parallel connected with the active transient voltage compensator 150 of 20 the present invention. A second filter capacitor C2 is connected across the DC-to-DC converter output as decoupling capacitors. The capacitor C2 and the equivalent series inductance L_{C2} and equivalent series resistance R_{C2} associated with capacitor C2 are illustrated as serially connected across 25 the output. The output of the DC-to-DC 100 incorporating the transient voltage compensator 150 according to the present invention are identified as output voltage V_o and output current Io. Alternative configuration for coupling the ATVC of the present invention with a DC-to-DC converter 30 will be obvious to those skilled in the art.

During transient periods, the equivalent inductance of the ATVC is approximately equal to the leakage inductance of the transformer, while maintaining normal inductance of winding N2 that is paralleled with the parasitic R_p and L_p 35 during steady state operation. At the same time the ATVC transformer T_r injects a serial positive voltage source to provide a high slew rate current with the input voltage. Conversely, in step-down load, the active transient voltage compensator transformer provides a serial negative voltage 40 to absorb high slew rate current with the output voltage. Using the transformer T_r , current handled by the ATVC is reduced, which contributes to a reduced conduction loss and switching loss in the ATVC.

There are three main modes for operation of the ATVC, 45 step-up load mode, steady-state mode, and step-down load mode. In step-up load mode, the imbalance between the main converter **110** output current I_1 and the DC-to-DC converter output current I_O results in a drop in the output voltage V_O . The decrease in the output voltage may even fall 50 out of the DC-to-DC converter specification output voltage requirement.

To overcome the problem, the ATVC **150** kicks in as a buck converter by controlling Q_{a1} with the driver signal **260** to compensate the output voltage V_O when the output 55 voltage V_O falls below the ATVC voltage V_{REF1} **221**. The driver signal of Qa**2 270** is complimentary with the driver signal of Qa**1 260** in step-up load mode.

The ATVC **150** of the present invention injects a high slew rate current, which is based on the transformer leakage 60 inductance L_{LK} and the difference between the ATVC **150** supply voltage V_1 and the DC-to-DC converter output voltage V_O as shown in FIG. **6**A. The primary current I_{N1} of the ATVC **150** transformer T_r freewheels through Q_{a2} when Qa1 is off as shown in FIG. **6**B. The primary current I_{N1} and 65 secondary current I_{N2} of transformer T_r together quickly catch up with the DC-to-DC converter output current I_O 6

because of the small value of the leakage inductance L_{LK} of the transformer T_r . Step-up load mode ends with the transformer T_r magnetizing current I_{LM} increasing to the maximum output current K·I_{max}. K is the current divider between Rp and R_{LM} in steady state mode.

FIG. 5 is a graphical representation of operational current and voltage waveforms of the DC-to-DC converter corresponding to the operational schematics of FIGS. 6A through 6D. The first waveform 210 in FIG. 5 is a graphical representation of the main converter 110 and DC-to-DC converter 100 output currents, I₁ and I₀. Referring to waveform 210, during step-up load mode the output current (I_{o}) 213 of the DC-to-DC converter 100 increases from minimum current (I_{min}) 212 to the maximum current (I_{max}) 216 during the time period t1 to t1'. Operation of the ATVC 150 corresponding to time period from t1 to t3 in step up mode is detailed only in one switching cycle operation, Qa1 is on and Qa2 is off from t1 to t1', Qa1 is off and Qa2 is on from t1' to t2, shown in the schematic of FIG. 6A and FIG. 6B. The ATVC 150 functions to sharply increase the ATVC current (I_{ATVC}) 230 from minimum current (K^*I_{min}) to the maximum current (K*I_{max}) during the time period t1 to t3 with the slowly increasing main converter output current (I_1) **214**. This is accomplished by biasing Q_{a1} "ON" and Q_{a2} "OFF" by the driver signal 260 and 270, providing an essentially low impedance path to allow current to flow from voltage source V_1 through transformer T_r primary N_1 . The transformer primary current I_{N1} and second current I_{N2} with magnetizing current I_{LM} increase the ATVC output current I_{ATFC} to catch up with the output current I_O as shown on waveforms 230, 240 and 250, respectively.

The ATVC continues to supply the current I_{ATVC} as shown in waveform **230** to maintain an output current I_o at I_{max} **216** from time t2 to t3 as the main converters current I_1 as identified on the graph of FIG. 5 by the ramped up dashed line **214**. Step-up load mode ends with the transformer T_r magnetizing current I_{LM} increasing to the current K*Imax.

With the introduction of the transformer T_r to the conventional DC-to-DC converter of the prior art shown in FIGS. 1 and 2, the active transient voltage compensator 150 of the present invention only handles a small current, resulting in a reduced conduction loss and switching loss in the active transient voltage compensation topology than that of the prior art current injection topology. The current handled by the active transient voltage compensator 150 is calculated according to K*Imax/(1+N) where N is the turn-ratio of the transformer (N=N1/N2). In step-up load mode, the active transient voltage compensator also provides high slew rate current, $(1+N)^*(V_1-V_{01})/L_{LK}$, approximately (1+N) times higher than that of switching mode current injection topology if the equivalent filter inductance is same.

In a steady-state mode, the time period on the graph of FIG. **5** between t**3** and t**4**, is schematically illustrated in FIG. **6**C. As shown, during steady-state Q_{a1} and Q_{a2} are biased off by the logic block **163** in the ATVC controller **164**. The current of I_{N1} and I_{N2} equals to zero and the current i_{LM} equals to K*Imax, K is the current divider ratio between R_P and R_{LM} . Design of the circuit to satisfy the following equation ensures that the active transient voltage compensator does not operate during the steady-state mode

 $N \cdot V_S < V_O - V_D$

65 where V_S is the transformer secondary voltage and V_D is the on-state voltage drop of body diode of synchronous rectifier Q_{a2} .

During the step-down load mode, the ATVC operates as a boost converter by controlling the operation of Q_{a2} from the step-down controller **162** in the ATVC controller **164** when the output voltage V_O is higher than the ATVC reference voltage V_{REF2} **223** as shown in waveform **220** of 5 FIG. **5**. The ATVC **150** recycles energy to the ATVC input voltage V1 during **t4** to **t6**, one switching cycle operation from **t4** to **t5** is detailed as shown in the schematic diagrams of FIGS. **6D** and **6E**. Referring to FIG. **6D**, during step-down load Qa**2** is biased to draw current I_{N1} from transformer 10 primary N₁ shown as a negative current in waveform **240**, to suppress the output voltage spikes and recycle energy to ATVC input voltage V₁. As shown by the decreasing dashed line **218**, the main converter output current I_1 decreases at a slower rate from time **t4** to **t6**. **15**

The driver signal of Qa1 as shown in 260 is complimentary with the driver signal of Qa2 as shown in 270 in step-down load mode. Referring to the operational schematic of FIG. 6E in conjunction with the graph of FIG. 5, from time t4' to time t5, the operation of the active transient 20 voltage compensator switches Q_{a1} "ON" and Q_{a2} "OFF", proving a path for transformer primary current I_{N1} to recycle energy to ATVC input voltage V1 to maintain the DC-to-DC converter output current I_O at I_{min} until the main converter current I_1 ramps down to I_{min} at time t6, as shown by the 25 dashed line 218 of waveform 210. Step down load mode terminates when with the transformer Tr magnetizing inductance current I_{LM} shown in waveform 250 decreasing to decreasing to output current K*Imin. Thus, during step-down load mode, when the main converter 110 output current I_1 30 exceeds I_{min} , the ATVC draws the excess current to maintain the DC-to-DC converter output current I_{Ω} approximately at I_{min} .

In step-down load mode, ATVC absorbs high slew rate current, $(1+N)*V_{02}/L_{LK}$, approximately (1+N) times higher 35 than that of switching mode current injection topology if the equivalent filter inductance is same. The handled current by ATVC is as 1/(1+N) times as much as the current of prior arts 14 and 16.

As described in the previous paragraphs corresponding to 40 FIGS. 5 and 6A-E, the active transient voltage compensator 150 operates in high frequency for small equivalent filter inductance, so it injects higher slew rate current in step-up load mode and recovers energy to the ATVC input voltage V_1 in the step-down load mode. The active transient voltage 45 compensator only operates in transient. The conduction loss of the transformer secondary winding N2 can be minimized by reducing the resistance of the transformer design. The inclusion of the active transient voltage compensator transformer T_r reduces the conduction losses and switching losses 50 of Qa1 and Qa2 during the transient periods compared with the higher power losses resulting from use of the prior art current injection methods. Moreover, the optimal design for improved efficiency is carried out in the main converter with improved transient response at lower high frequency opera- 55 tion.

In summary, the present invention provides a method, system apparatus and device for improving the fast transient response of a DC-to-DC converter using the active transient voltage compensator (ATVC) topology of the present invention. The ATVC injects high slew rate current in step-up load and recovers energy during step-down load. The introduction of a transformer in the ATVC circuit reduces the compensator channel's conduction loss and switching loss. The ATVC operates during transient periods to eliminate the 65 effect of parasitic inductance that is series with ATVC resulting from voltage injection. The ATVC also achieves a

wide bandwidth instead of pushing the main converter into high frequency operation to improve the main converters efficiency and maintains the converters output impedance while reducing the bulk capacitors.

EXPERIMENT

An experiment according to the DC-to-DC converter shown in the schematic diagram of FIG. 7 was carried out in the laboratory with a power distribution model for the processor with voltage regulator (VR), which was provided in VR10.0 by Intel. The DC-to-DC converter includes a main converter, filter circuit and incorporates the ATVC of the present invention between the main converter and the load. A three-phase VR and active transient voltage compensator are provided in parallel between inductor L1 and inductor L2 in the power distribution model. VR operates at 250 KHz and the ATVC is operated at 2.5 MHz. The experimental circuit is provided with a supply voltage V_{IN} =12VDC, an output voltage V_{o} =1.1VDC, an output current I_{o} between I_{max} =100 amps and I_{min} =10 amps which is supplied to the load.

VRM10.0 defines dc-dc converters to meet the power supply requirements of desktop computer systems, which output voltage is 0.8375V~1.6000V with VID control code, and its current is up to 120 A; the output current slew rate for CPU is up to 1-2 A/ns. The socket load lines contain dc load line and transient load line as well as maximum and minimum voltage levels, which are measured at the processor socket dedicated pins between the voltage regulator and processor cavity.

FIG. 8 illustrates the operational currents of the ATVC circuit including the transformer T_r primary current I_{N1} , secondary current I_{N2} , the magnetizing inductance current I_{LM} and the ATVC output current I_{ATVC} during step-up load mode. As shown, the ATVC circuit provides a higher slew rate positive current I_{ATVC} during step-up load mode. Conversely, the operational currents provided by the ATVC during step-down load mode are shown in FIG. 9. As shown, the ATVC circuit provides a high slew rate negative current to recycle energy into the input voltage V_1 during step-down load mode operation.

FIGS. **10** and **11** show a comparison between the ATVC operational current I_{ATVC} , the main converter output current I_0 during step-up load mode and step-down load mode, respectively. As shown in FIG. **10**, the ATVC provides a higher slew rate current I_{ATVC} than the output current I_1 provided by the main converter. According to the graph plotted in FIG. **10**, the ATVC current I $_{ATVC}$ times faster than the main converter output current to increase the output current I_0 from $I_{min}=10$ amps to $I_{max}=100$ amps. Likewise, during step-down load mode, the slew rate of the current provided by the ATVC decreases approximately five times faster than the main converter output current I_1 as the ATVC recycles energy into the input voltage source for improved efficiency.

FIGS. **12**A and **12**B are graphs of the DC-to-DC converter output voltage V_O during step-up load mode with ATVC and without ATVC, respectively. As shown in FIG. **12**B, during step-up load mode without ATVC the output voltage VO includes two spikes. The first spike is the result of performance of capacitors and layout, ESR and ESL while the second spike is mainly determined by the closed loop design of the circuit. When the DC-to-DC converter incorporates the ATVC of the present invention, an improvement in the second voltage spike is shown in FIG. **12**A. Similarly, an improvement in the second spike is observed when the graph of the output voltage Vo during step-down load mode without ATVC (FIG. 13B) is compared to the output voltage VO with ATVC as shown in FIG. **13**A.

While the method, system, apparatus and device of the 5 present invention has been illustrated and discussed when utilized the DC-to-DC converter as shown in FIG. 4, the ATVC mat be utilized in other DC-to-DC converters, including but not limited to, the DC-to-DC converters circuits shown in FIGS. 14, 15 and 16. FIGS. 15 and 16 are 10 schematic diagram of an isolated DC-to-DC converter using the ATVC of the present invention to improve transient response without pushing high frequency operation for the main isolated converter where Rp and Lp represent the parasitic parameters.

While the invention has been described, disclosed, illustrated and shown in various terms of certain embodiments or modifications which it has presumed in practice, the scope of the invention is not intended to be, nor should it be deemed to be, limited thereby and such other modifications 20 or embodiments as may be suggested by the teachings herein are particularly reserved especially as they fall within the breadth and scope of the claims here appended.

We claim:

25 1. A direct current to direct current (DC-to-DC) converter having an improved fast transient response, the converter comprising:

- a DC-to-DC main converter having an input terminal and a DC output terminal with a first and second capacitor 30 connected across the output terminal; and
- an active transient voltage compensator (ATVC) connected in parallel with the output terminal between the first and second capacitor, the active transient voltage compensator comprising:
 - 35 a transformer having a primary winding and a secondary winding, one end of the secondary winding connected to one end of the first capacitor to provide a stepped inductance during the transient operation to compensate the output voltage while maintaining $_{40}$ normal inductance during the steady state operation;
 - a switching circuit having a step-up synchronous rectifier and a step-down synchronous rectifier connected with one end of the transformer primary for controlling a transformer current, the other end of the 45 primary and secondary connected to one end of the second capacitor; and
 - an ATVC controller connected to the ATVC for monitoring the output voltage and producing a driver signal for activating one of the step-up and step- 50 down synchronous rectifiers to inject a voltage source to compensate the output voltage when the output voltage falls below an ATVC reference voltage and increases above the reference voltage, respectively, to compensate the DC output terminal 55 output voltage during a transient operation without switching loss during a steady-state operation.

2. The converter of claim 1, wherein the ATVC controller comprises:

- a step-up control with the reference voltage for step-up 60 mode, and
- a step-down control with the reference voltage for stepdown mode, and
- a logic block to control no ATVC operation in steady state and normal operation in transient, wherein the ATVC 65 injects the voltage source to improve transient response of the DC-to-DC converter.

3. The converter of claim 1, wherein the ATVC operates as a buck converter to compensate the output voltage when the output voltage falls below an ATVC reference voltage.

4. The converter of claim 1, wherein the ATVC operates as a boost converter to recycle a DC output terminal energy when the output voltage exceeds and ATVC reference voltage.

5. The converter of claim 1, wherein the DC-to-DC converter is an isolated DC-to-DC converter, wherein the ATVC improves transient response without pushing high frequency operation for the main converter.

6. The improved converter of claim 1, wherein the DC-to-DC converter is a non-isolated DC-to-DC converter.

7. A method for improving transient response for direct current to direct current (DC-to-DC) converter, the method comprising the steps of:

- connecting a first and second capacitor and an active transient voltage compensator (ATVC) in parallel with the main converter, the ATVC connected between the first and second capacitor; and
- injecting a voltage source during step-up load mode and step-down load mode to improve transient response during transient operation to compensate an output voltage to maintain output voltage requirements, wherein the ATVC handles a small current in transient loads that results in a reduction of conduction and switching losses and improves the injected current slew rate.
- 8. The method of claim 7, wherein the voltage injection step comprises the steps of:
 - comparing a DC converter output voltage to an ATVC reference voltage;
- when the DC converter output voltage is less than the ATVC reference voltage, operating the ATVC as the buck converter to increase the first converter output current to achieve the maximum current; and
- when the DC converter output voltage is greater than the ATVC reference voltage, operating the ATVC as the boost converter to decrease the first converter output current to achieve the minimum current, wherein the ATVC compensates the output voltage to maintain output voltage specification requirements.

9. The method of claim 8, wherein the buck converter operation step comprises the steps of:

- providing a current path for conducting a forward ATVC current through the ATVC; and
- providing a coupler with the ATVC for coupling the forward ATVC current with the first converter output current to achieve the maximum output current.

10. The method of claim 8, wherein the buck converter operation step comprises the steps of:

- providing a first path for routing a first ATVC current through the ATVC;
- coupling the first ATVC current with the first converter output current to produce a second converter output current;
- terminating the first path when the second converter output current reaches a maximum output current;
- providing a second path for routing a second ATVC current through the ATVC;
- coupling the second ATVC current with the converter output current to maintain the an output voltage within converter specifications; and

15

terminating the second path when the first converter output current is substantially equal to the maximum output current.

11. The method of claim 7, wherein the boost converter $_5$ operation step comprises the steps of:

providing a first path for routing a first reverse current through the ATVC;

terminating the first path when the second converter output current reaches the minimum output current;

- providing a second path for routing a second reverse current through the ATVC; and
- terminating the second path when the first converter output current is substantially equal to the minimum output current.

* * * * *